AD-A060 227 NAVY UNDERWATER SOUND LAB NEW LONDON CONN F/G 17/1
THE OUTPUT OF A TRUE CORRELATOR WITH NOISY INPUTS.(U)
SEP 66 E S EBY
UNCLASSIFIED USL-TM-2242-244-66 NL

| OF |
AD
A060227

END
DATE
FILMED
12-78
DDC

NW Good

MOST Project -3

(14) USL-TM-2242-244-66

Copy 9

Code 2064.2

USL Problem
No. 7-1-410-00-00

U. S. Navy Underwater Sound Laboratory
Fort Trumbull, New London, Connecticut

(6) THE OUTPUT OF A TRUE CORRELATOR WITH NOISY INPUTS.

by

(10) Edward S./ Eby

USL Technical Memorandum No. 2242-244-66

(11) 7 Sep~~tember 19~~66

Consider the true correlator of the figure with noisy inputs:

$$r_1(t) = s(t) + n_1(t)$$

(9) Technical memo.,

$$r_2(t) = s(t) + n_2(t)$$

where $s(t)$ is a signal common to both inputs and $n_1(t)$, $n_2(t)$ are noise waveforms.

$$\begin{array}{l} r_1(t) = s(t) + n_1(t) \longrightarrow \\ r_2(t) = s(t) + n_2(t) \longrightarrow \end{array} \boxed{\text{True Correlator}} \longrightarrow \rho(\tau)$$

Figure (12) 3p.

LEVEL II

The output of the correlator is

$$(1) \quad \rho(\tau) = \frac{\int_{-\infty}^{\infty} r_1(t)\, r_2(t+\tau)\, dt}{\left[\int_{-\infty}^{\infty} r_1^2(t)\, dt \cdot \int_{-\infty}^{\infty} r_2^2(t)\, dt\right]^{\frac{1}{2}}}$$

Assume the signal is not correlated with either noise and let

$$S = \int_{-\infty}^{\infty} s^2(t)\, dt = \text{signal power}$$

$$N_i = \int_{-\infty}^{\infty} n_i^2(t)\, dt = i^{th} \text{ noise power, } i = 1,2$$

2242-244-66

001786

AF-13

254 200

Encl (7)

Then

$$(2)\qquad \rho(t) = \frac{\int_{-\infty}^{\infty}(s(T) + n_1(T))\,(s(t+T) + n_2(t+T))dT}{\left[\int_{-\infty}^{\infty}(s(t) + n_1(t)^2 dt \cdot \int_{-\infty}^{\infty}(s(t) + n_1(t))^2 dt\right]^{\frac{1}{2}}}$$

Evaluation of the integrals gives

$$(3)\qquad \rho(t) = \frac{S\,\rho_{ss}(t) + (N_1N_2)^{\frac{1}{2}}\,\rho_{n_1n_2}(t)}{\left[(S+N_1)\;(S+N_2)\right]^{\frac{1}{2}}}$$

which we can write as

$$(4)\qquad \rho(t) = \frac{(S/N_1)^{\frac{1}{2}}\,(S/N_2)^{\frac{1}{2}}\,\rho_{ss}(t) + \rho_{n_1n_2}(t)}{\left[\,(1 + S/N_1)\;(1 + S/N_2)\right]^{\frac{1}{2}}}$$

or

$$(5)\qquad \rho(t) = \frac{\rho_{ss}(t) + (N_1/S)^{\frac{1}{2}}\,(N_2/S)^{\frac{1}{2}}\,\rho_{n_1n_2}(t)}{\left[(1 + N_1/S)\;(1 + N_2/S)\right]^{\frac{1}{2}}}\,.$$

If both signal-to-noise ratios are large ($S/N_i >> 1$ or $N_i/S << 1$, $i = 1,2$) we can use the approximation, ignoring terms higher than the first power,

$$(6)\qquad \rho(t) \simeq \left[1-\tfrac{1}{2}(N_1/S + N_2/S)\right]\rho_{ss}(t) + (N_1/S)^{\frac{1}{2}}\,(N_2/S)^{\frac{1}{2}}\;n_1n_2(t),$$

if both signal-to-noise ratios are small ($S/N_i << 1$, $i = 1,2$), then the approximation becomes

$$(7)\qquad \rho(t) = (S/N_1)^{\frac{1}{2}}\,(S/N_2)^{\frac{1}{2}}\,\rho_{ss}(t) + \left[1-\tfrac{1}{2}(S/N_1+S/N_2)\right]\rho_{n_1n_2}(t).$$

If one signal-to-noise ratio is high and the other is low (say $S/N_1 \gg 1, S/N_2 << 1$) then

$$(8)\qquad \rho(t) = \frac{(S/N_2)^{\frac{1}{2}}\,\rho_{ss}(t) + (N_1/S)^{\frac{1}{2}}\,\rho_{n_1n_2}(t)}{\left[(1 + N_1/S)\;(1 + S/N_2)\right]^{\frac{1}{2}}}$$

give the approximation, ignoring powers higher than the first,

$$(9)\qquad \rho(t) \approx (S/N_2)^{\frac{1}{2}} \rho_{ss}(t) + (N_1/S)^{\frac{1}{2}} \rho_{n_1 n_2}(t).$$

Hence, for high signal-to-noise ratios, the correlator output $\rho(\tau)$ approximates the signal autocorrelation $\rho_{ss}(\tau)$, for low signal-to-noise ratios $\rho(\tau)$ follows the noise correlation $\rho_{n_1 n_2}(\tau)$, and in the mixed case, the correlator output is mixed. In fact, if both signal-to-noise ratios are unity (0db), the true correlator output is just the arithmetic mean of the signal and noise correlations

$$(10)\qquad \rho(t) = \frac{\rho_{ss}(t) + \rho_{n_1 n_2}(t)}{2} .$$

From the above calculation, we see that the correlator output will decrease in amplitude in the presence of noise, even if the noise cross-correlation is zero. If the noise correlation does not vanish, then this will appear as a bias on the true correlator output.